

# KINELEC

18-50W DC-AC Inverter

# DCAC-1



### Features :

- Input Voltage Range 12-48VDC
- Protections: Short circuit/ overload/OV
- Battery Reverse Protection
- Output available 110-230VAC 50 Hz
- 1 year warranty

## DC-AC INVERTER

(Also available in U racks)

Dimension 170 x 220 x 80 mm (L- W - H)

MODEL No	VOLTAGE IN	VOLTAGE OUT	RATED CURRENT (Approx)	RATED POWER	LOAD REGULATION
KSEDCAC18W01	12VDC	110	.164	18W	10V
KSEDCAC18W02	12VDC	230	.0820	18W	10V
KSEDCAC18W03	18VDC	110	.164	18W	10V
KSEDCAC18W04	18VDC	230	.0820	18W	10V
KSEDCAC18W05	24VDC	110	.164	18W	10V
KSEDCAC18W06	24VDC	230	.0820	18W	10V
KSEDCAC18W07	36VDC	110	.164	18W	10V
KSEDCAC18W08	36VDC	230	.0820	18W	10V
KSEDCAC18W09	48VDC	110	.164	18W	10V
KSEDCAC18W10	48VDC	230	.0820	18W	10V
KSEDCAC50W11	12VDC	110	.455	50W	10V
KSEDCAC50W12	12VDC	230	.227	50W	10V
KSEDCAC50W13	18VDC	110	.455	50W	10V

KSEDCAC50W14	18VDC	230	.227	50W	10V
KSEDCAC50W15	24VDC	110	.455	50W	10V
KSEDCAC50W16	24VDC	230	.227	50W	10V
KSEDCAC50W17	36VDC	110	.455	50W	10V
KSEDCAC50W18	36VDC	230	.227	50W	10V
KSEDCAC50W19	48VDC	110	.455	50W	10V
KSEDCAC50W20	48VDC	230	.227	50W	10V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.