

# KINELEC

## 36W DC-DC Single Output Desktop Type

# DC DTT-3



### Features :

- Input Voltage Range 9-56VDC
- Protections: Short circuit/ overload/ over voltage,CC,CV
- Input Reverse Protection
- Output available 5-56VDC
- Output lead approx 1 mtr with DC Pin
- Input Lead approx 10 inch with connector strip
- Rugged Plastic Body
- 1 year warranty

### DC-DC CONVERTER DESKTOP TYPE

(Also available in open card)

Dimension 123 x 62 x 42 mm (L- W - H)

Wt. 240 gms. (Approx)

MODEL No	VOLTAGE IN	VOLTAGE OUT	RATED CURRENT (Approx)	RATED POWER	LOAD REGULATION
KSEDCDC36W01	9VDC	5	4	36W	.1-.3V
KSEDCDC36W02	9VDC	7.5	4	36W	.1-.3V
KSEDCDC36W03	9VDC	9	4	36W	.1-.3V
KSEDCDC36W04	9VDC	12	3	36W	.1-.3V
KSEDCDC36W05	9VDC	15	2.4	36W	.1-.3V
KSEDCDC36W06	9VDC	18	2	36W	.1-.3V
KSEDCDC36W07	9VDC	24	1.5	36W	.1-.3V
KSEDCDC36W08	9VDC	48	0.750	36W	.1-.3V
KSEDCDC36W09	9VDC	56	0.650	36W	.1-.3V
KSEDCDC36W10	12VDC	5	4	36W	.1-.3V
KSEDCDC36W11	12VDC	7.5	4	36W	.1-.3V
KSEDCDC36W12	12VDC	9	4	36W	.1-.3V
KSEDCDC36W13	12VDC	12	3	36W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.

KSEDCDC36W14	12VDC	15	2.4	36W	.1-.3V
KSEDCDC36W15	12VDC	18	2	36W	.1-.3V
KSEDCDC36W16	12VDC	24	1.5	36W	.1-.3V
KSEDCDC36W17	12VDC	48	0.750	36W	.1-.3V
KSEDCDC36W18	12VDC	56	0.650	36W	.1-.3V
KSEDCDC36W19	18VDC	5	4	36W	.1-.3V
KSEDCDC36W20	18VDC	7.5	4	36W	.1-.3V
KSEDCDC36W21	18VDC	9	4	36W	.1-.3V
KSEDCDC36W22	18VDC	12	3	36W	.1-.3V
KSEDCDC36W23	18VDC	15	2.4	36W	.1-.3V
KSEDCDC36W24	18VDC	18	2	36W	.1-.3V
KSEDCDC36W25	18VDC	24	1.5	36W	.1-.3V
KSEDCDC36W26	18VDC	48	0.750	36W	.1-.3V
KSEDCDC36W27	18VDC	56	0.650	36W	.1-.3V
KSEDCDC36W28	24VDC	5	4	36W	.1-.3V
KSEDCDC36W29	24VDC	7.5	4	36W	.1-.3V
KSEDCDC36W30	24VDC	9	4	36W	.1-.3V
KSEDCDC36W31	24VDC	12	3	36W	.1-.3V
KSEDCDC36W32	24VDC	15	2.4	36W	.1-.3V
KSEDCDC36W33	24VDC	18	2	36W	.1-.3V
KSEDCDC36W34	24VDC	24	1.5	36W	.1-.3V
KSEDCDC36W35	24VDC	48	0.750	36W	.1-.3V
KSEDCDC36W36	24VDC	56	0.650	36W	.1-.3V
KSEDCDC36W37	48VDC	5	4	36W	.1-.3V
KSEDCDC36W38	48VDC	7.5	4	36W	.1-.3V
KSEDCDC36W39	48VDC	9	4	36W	.1-.3V
KSEDCDC18W40	48VDC	12	3	36W	.1-.3V
KSEDCDC36W41	48VDC	15	2.4	36W	.1-.3V
KSEDCDC36W42	48VDC	18	2	36W	.1-.3V
KSEDCDC36W43	48VDC	24	1.5	36W	.1-.3V
KSEDCDC36W44	48VDC	48	0.750	36W	.1-.3V
KSEDCDC36W45	48VDC	56	0.650	36W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.

KSEDCDC36W46	56VDC	5	4	36W	.1-.3V
KSEDCDC36W47	56VDC	7.5	4	36W	.1-.3V
KSEDCDC36W48	56VDC	9	4	36W	.1-.3V
KSEDCDC36W46	56VDC	12	3	36W	.1-.3V
KSEDCDC36W47	56VDC	15	2.4	36W	.1-.3V
KSEDCDC36W48	56VDC	18	2	36W	.1-.3V
KSEDCDC36W46	56VDC	24	1.5	36W	.1-.3V
KSEDCDC36W47	56VDC	48	0.750	36W	.1-.3V
KSEDCDC36W48	56VDC	56	0.650	36W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.