

# KINELEC

## 18W DC-DC Single Output Desktop Type

# DC DTT-2



### Features :

- Input Voltage Range 9-56VDC
- Protections: Short circuit/ overload/ over voltage,CC,CV
- Input Reverse Protection
- Output available 5-56VDC
- Output lead approx 1 mtr with DC Pin
- Input Lead approx 10 inch with connector stip
- Rugged Plastic Body
- 1 year warranty

### DC-DC CONVERTER DESKTOP TYPE

(Also available in open card)

Dimension 105 x 49 x 32 mm (L- W - H)

Wt. 170 gms. (Approx)

MODEL No	VOLTAGE IN	VOLTAGE OUT	RATED CURRENT (Approx)	RATED POWER	LOAD REGULATION
KSEDCDC18W01	9VDC	5	3.5	18W	.1-.3V
KSEDCDC18W02	9VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W03	9VDC	9	2	18W	.1-.3V
KSEDCDC18W04	9VDC	12	1	18W	.1-.3V
KSEDCDC18W05	9VDC	12	1.5	18W	.1-.3V
KSEDCDC18W06	9VDC	12	2	18W	.1-.3V
KSEDCDC18W07	9VDC	15	1.2	18W	.1-.3V
KSEDCDC18W08	9VDC	18	1	18W	.1-.3V
KSEDCDC18W09	9VDC	24	1	18W	.1-.3V
KSEDCDC18W10	12VDC	24	0.750	18W	.1-.3V
KSEDCDC18W11	12VDC	48	0.400	18W	.1-.3V
KSEDCDC18W12	12VDC	56	0.320	18W	.1-.3V
KSEDCDC18W13	12VDC	5	3.5	18W	.1-.3V
KSEDCDC18W14	12VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W15	12VDC	9	2	18W	.1-.3V
KSEDCDC18W15	12VDC	12	1.5	18W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.

KSEDCDC18W14	12VDC	15	1.2	18W	.1-.3V
KSEDCDC18W15	12VDC	18	1	18W	.1-.3V
KSEDCDC18W16	12VDC	24	0.750	18W	.1-.3V
KSEDCDC18W17	12VDC	48	0.400	18W	.1-.3V
KSEDCDC18W18	12VDC	56	0.320	18W	.1-.3V
KSEDCDC18W19	18VDC	5	3.5	18W	.1-.3V
KSEDCDC18W20	18VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W21	18VDC	9	2	18W	.1-.3V
KSEDCDC18W22	18VDC	12	1.5	18W	.1-.3V
KSEDCDC18W23	18VDC	15	1.2	18W	.1-.3V
KSEDCDC18W24	18VDC	18	1	18W	.1-.3V
KSEDCDC18W25	18VDC	24	0.750	18W	.1-.3V
KSEDCDC18W26	18VDC	48	0.400	18W	.1-.3V
KSEDCDC18W27	18VDC	56	0.320	18W	.1-.3V
KSEDCDC18W28	24VDC	5	3.5	18W	.1-.3V
KSEDCDC18W29	24VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W30	24VDC	9	2	18W	.1-.3V
KSEDCDC18W31	24VDC	12	1.5	18W	.1-.3V
KSEDCDC18W32	24VDC	15	1.2	18W	.1-.3V
KSEDCDC18W33	24VDC	18	1	18W	.1-.3V
KSEDCDC18W34	24VDC	24	0.750	18W	.1-.3V
KSEDCDC18W35	24VDC	48	0.400	18W	.1-.3V
KSEDCDC18W36	24VDC	56	0.320	18W	.1-.3V
KSEDCDC18W37	48VDC	5	3.5	18W	.1-.3V
KSEDCDC18W38	48VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W39	48VDC	9	2	18W	.1-.3V
KSEDCDC18W40	48VDC	12	1.5	18W	.1-.3V
KSEDCDC18W41	48VDC	15	1.2	18W	.1-.3V
KSEDCDC18W42	48VDC	18	1	18W	.1-.3V
KSEDCDC18W43	48VDC	24	0.750	18W	.1-.3V
KSEDCDC18W44	48VDC	48	0.400	18W	.1-.3V
KSEDCDC18W45	48VDC	56	0.320	18W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.

KSEDCDC18W46	56VDC	5	3.5	18W	.1-.3V
KSEDCDC18W47	56VDC	7.5	2.2	18W	.1-.3V
KSEDCDC18W48	56VDC	9	2	18W	.1-.3V
KSEDCDC18W49	56VDC	12	1.5	18W	.1-.3V
KSEDCDC18W50	56VDC	15	1.2	18W	.1-.3V
KSEDCDC18W51	56VDC	18	1	18W	.1-.3V
KSEDCDC18W52	56VDC	24	0.750	18W	.1-.3V
KSEDCDC18W53	56VDC	48	0.400	18W	.1-.3V
KSEDCDC18W54	56VDC	56	0.320	18W	.1-.3V

In addition to the above voltage range, we can provide you with specific voltage as desired by you.